

Zeta Magnetic Door Holders

(ZT-DR24 & ZT-DR240)



The Zeta magnetic door holders are designed to retain a fire door open against the force of its own closing device. In the event of a fire, the door holder magnet can be turned off by the fire alarm, allowing the door to shut.

The manual release button is changeable from the base side to left or right. Cable entry is possible from rear side by means of enclosed exits from the base side, left or right.

An optional bracket is also available for floor or wall mounting (ZT-BR).



ZT-BR

Features

- ✓ Tested according to EN1155

Model	ZT-DR24	ZT-DR240
Part No.	50-001	50-002
Rated Voltage	24V DC	230V AC
Rated Current	65mA	6mA
Switch Through Aux	Yes	No
Needs Back EMF Diode	Yes	No
Holding Force	400 N	
Size (Main Unit)	110 x 85 x 38mm	
Dimensions (Keeper Plate)	55 x 55 x 50mm	
Weight (Main Unit)	404g	
Weight (Keeper Plate)	153g	