

Desktop microphone with pre chime DIGIM1



Part-No. 586102

Desktop call station built-in pre chime DIGI M1. 1 writable button with LED indicator for keyboard control and busy /operating-/chime display. Processor control with programming via diodes. Integrated limiter and special circuit to eliminate thumps. Built-in + 6 dB NF-amplifier with volume control. Concise short chime with controls for volume and pitch. Parallel connection of up to 40 call stations on line JY(ST)Y6 (4) x 2 x 0.8 (0.6). 3 m connecting cable with D-Sub-plug 9-pin. Cardioid swan-neck in electret condenser technology.

Operating voltage	24 V DC
Current consumption @ 24 V DC	approx. 24 mA
Housing	ABS light gray
Dimensions	L: 250 mm W: 125 mm H: 30 mm D: 150 mm